

Vonino iMart QSL Windows 10 Installation





1. Pre-requsite for S/W Downloading

Downloading files	Download Windows10.rar archive from: <u>ftp://ftp.vonino.org/public/Firmware/Voni</u> <u>no Tablets/iMart QSL/</u>
USB Hub (at least 4 USB ports)	
USB Keyboard	
USB Memory Stick (at least 8GB)	DataTraveler® 64 16ce





2. S/W Downloading

2.1 Making bootable the USB Stick

- Insert the USB stick in PC
- Extract the Windows10.rar archive. From **Tool** folder Run As Administrator **UltralSO_v9.5.2.2836**



Copyright © 2013 VONINO Inc.



• Select the **Open** icon and open **winpe_x86_win10.iso.**

Select the option	ons like in th	e picture below						
🕥 UltraISO - E:\Soft	t\last_firmware_1\W	/indows 10_Ployer\Tool\wing	oe_x86_win10.iso			_		\times
Îļþ(F) ²Ù×÷(A)	Æô¶⁻(B) ¹ ¤³⁄4ß(T) Ñ¡lî(O) °ïÖú(H)						
🗋 🤌 - 💩 🔒	لالله ÖÆ×÷ÈíÅÌÓ³Ĩñ	ÎĂ¼þ	🕘 🕕 大小总计:	198MB 30%	of 65	0MB - 4	52MB fre	e
光盘目录: 2.60	Đ'EĕEíAlOʻlñ		路径:/					
	ÖÆ×÷Ó²ÅÌÓ³ï	ñÎļb						
	Ð′ÈëÓ²ÅÌÓ³Ĩñ		οĐ,	Yaðl		EOÆU/E	±%ä	
	(624)(621)(62		76 KB	文件夹		2015-0	7-18 08:	31
cs=cz	OEIAI/O-AIÇŷ	AE÷laE¦Oýµ¼EEÇø	20, 839 KB	文件夹		2015-0	7-18 08:3	31
dadk	'O CD/DVD láE	¡Οýμ¼ΙΑ¼þ	75 KB	文件夹		2015-0	7-18 08:	31
	🕸 ¼ÓÔØÒýu¼Ìį	ļh	75 KB	文件夹		2015-0	7-18 08:	31
🗄 💼 EFI	+f'>Ovu1/(Å1/	(h	78 KB	文件夹		2015-0	7-18 08:	31
el-gr	22 æ0yµ/4A/	•p	18,151 KB	文件夹		2015-0	7-18 08:	31
en-gb		¢	79 KB	文件夹		2015-0	7-18 08:	31
en-us	Éú³ÉÆô¶⁻ÐÅÏ¢	±í	73 KB	文件夹		2015-0	7-18 08:	31
es-es	🛞 ÖÆ×÷¶àÖØÆ	ô¶ ⁻¹ âuú	73 KB	文件夹		2015-0	7-18 08:	31
es-mx			76 KB	文件夹		2015-0	7-18 08:	31
et-ee fi-fi	~	in estax	76 KB			2015-0	7-18 08:	31 *
本地目录:		🍺 📂 🗙 🗔 餐 🏶 🖻	路径: C: \					
□	^	ĬĀ×þāû	´óĐ,	ÀàĐÍ		ÊÔÆÚ/Ê	±%ä	^
I IIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIII	BIN	📄 \$RECYCLE. BIN		文件夹	!	2016-02	2-09 08:	43
	BT	🛅 \$WINDOWS. "BT		文件夹		2016-0	5-27 11:	11
tindows.	wэ	🛅 \$Windows. ~WS		文件夹	!	2016-0	5-27 11:	11
		🛅 apps		文件夹		2014-09	9 29 03 :r	09
Documents	s and Settings	🛅 DELL		文件夹		2014-09	9-29 04::	22
🕀 🦳 Drivers		🛅 Documents and Setting	<u>s</u>	文件夹	!	2013-08	8-22 17:	45
i fx		🛅 Drivers		文件夹		2014-09	9 - 29 03:0	09
🕕 🫅 Intel		🛅 i fx		文件夹		2016-04	4-22 23:	18
🕴 🛱 🦳 ManiMETA	тла 🗡	🖨 Totel		文件卖		2016-03	2-02-04-1	58 ×
<	>	<						>
	旨 (c)2002-2011 EZ	B Systems, Inc		1340 KB 木	御日雪	・8文借	E. 3009 1	MB

• Select the options like in the picture below



- UltraISO - E:\Soft\last_firmware_1\Windows 10_Ployer\Tool\winpe_x86_win10.iso × Ĩļþ(F) ²Ù×÷(A) Æô1T(B) ¹ថ₃₄ឩ(T) Ñijî(O) °ĩÕᡤ(H). Ð'ÈëÓ²ÅÌÓ³Ïñ \times 📄 🤌 🗕 😓 free ±£´æ LÉÔγ́μX' âĂÌ 消息: 光盘目录: 时间 事件 💽 DVD_ROM ~ 🛅 bg-bg Windows 6.2 Build 9200 8:31 🗄 🛅 Boot PM 05:09:58 KingstonDataTraveler 3.0PMAP)8:31 🛅 osmoz)8:31 🛅 da-dk)8:31 🛅 de-de)8:31 🗄 🛅 EFI)8:31 🛅 el-gr)8:31 🛅 en-gb)8:31 🛅 en-us < >)8:31 📄 es-es)8:31 🚞 es-m x 硬盘驱动器: (G:, 15 GB)KingstonDataTraveler 3.0PMAP \sim 🔜 21AXУÑé 18÷31 ≯ 🛅 et-ee 🛅 fi-fi 映像文件: E:\Soft\last_firmware_1\Windows 10_Ployer\Tool\winpe_x86_wi: 本地目录: 写入方式: USB-HDD+ 🖮 😰 我的ISO文档 ±à%ÝÆô¶¯ \sim ^ 🗄 🛅 \$RECYCLE. BIN)8:43 🗄 🍋 \$WINDOWS. ~BT 🗹 ´´ %… £ô¶¯ • ŌÇø Éî¶ÊÔþ'Ø 1:11 🗄 🫅 \$Windows. ~WS 1:11 完成比例: 0% 00:00:00 🗄 🛅 apps 已用时间: 00:00:00 剩余时间:)3:09 🛓 🛅 DELL)4:22 🛅 Documents and Sett 7:45 OKB/s 🗄 🛅 Drivers 速度: 🛁 i fx)3:09 000' [A] ñʉ дÈë 23:18 🗄 🛅 Intel • µ»Ø 📩 🦳 ManiMETA LOG 14 : 58 > < 版权所有 (a)2002-2011 EZB Systems, The 半母日录・2 文件、1340 KB 木神日录・8 文件、3009 MB
- Make sure that all the settings are like in the picture below and select the blue marked button and press Yes

- After the process is done, close the program.
- The USB stick will be named **DVD_ROM**



Format the USB stick with the following settings:
 Select NTFS in File system
 -change the Volume label in WINPE

Format DVD_ROM (G:)	×
Capacity:	_
14.2 GB	~
<u>F</u> ile system	ר
NTES	~
Allocation unit size	
4096 bytes	\sim
Restore <u>d</u> evice defaults	
Volume label	ר
Volume <u>l</u> abel WINPE	
Volume label WINPE Format options	
Volume <u>l</u> abel WINPE Format <u>options</u>	J
Volume label WINPE Format options Quick Format	J
Volume label WINPE Format options Quick Format	5
Volume label WINPE Format options Quick Format	
Volume label WINPE Format gptions Quick Format	
Volume label WINPE Format gptions Quick Format	

• Copy all the files from **Kit 2** folder in the root of the **WINPE** memory stick.



• Connect the WINPE memory stick on the USB hub and the keyboard.



Attention! Make sure that the iMart QSL tablet is charged at least 70%.

- Connect the USB hub at the USB port on iMart QSL tablet.
- To enter in Boot Manager press **Esc** key on the keyboard simultaneous with the **Power On** key on the iMart QSL tablet.



• When the tablet powers on, release the Power On key and stil press Esc.





• With the scroll keys on the keyboard select Boot Manager.







• Select the USB stick (the tablet will restart).

The installing process will begin.
 CAUTION! Do not disconnect the usb hub during the installation.



Copyright © 2013 VONINO Inc.



• After the installing process is done the tablet will restart and enter in Administrator Mode.



• On the System Preparation Tool window select OK (the tablet will restart).

System Preparation To	ol 3.14	×
System Preparation To hardware independence	ol (Sysprep) prepares the mad e and deanup.	hine for
System Cleanup Actic Enter System Out-of Generalize	n -Box Experience (OOBE)	~
Shutdown Options Reboot		-
	ОК	Cancel

Copyright © 2013 VONINO Inc.



• Process Done.

